

# ИИ-12А, ИИ-12Б Mass 20g

Plates-figures (0-9)in the ИИ12А

figures (0-9) and comma in the ИИ12Б

The first electrode marked by white colour inside the tube.

The next electrodes are counting from left to right from this first electrode as goes the clock's hand.

The pins of electrodes:

1-plate 7-figure 5

2-figure 0 8-figure 4

3-figure 9 9-figure 3

4-figure 8 10-figure 2

5-figure 7 11-figure 1

6-figure 6 12-comma in the ИИ12Б

in the ИИ12А is not connected

Technical specifications:

Brightness  $\geq 100\text{Kd/m}^2$

Power supply voltage  $\geq 200\text{V}$

Voltage of the indication :

of figures  $\leq 2\text{mA}$

of comma  $\leq 0.3\text{mA}$

Lighting voltage  $\leq 170\text{V}$

Operating voltage  $\leq 150\text{V}$

The operation voltage from the DC supplier:

of figures 2-3.5mA

of comma 0.3-0.7mA

The operation voltage from the AC supplier:

of figures 1-2mA

of comma 0.15-0.2mA

Capacity of work 7500hours

